Protecting the Important Things in Your Life.

New Product Information: WO 500

2.4 GHz Wireless B/W Camera and 5” Monitor

Here’s the perfect solution when you need to be in two places at the same time… use a Home Sentinel wireless video monitoring system to give you an extra “set of eyes”.

This is an ideal product for monitoring children around the house… simply plug in the camera where it can watch over junior at play, and move the monitor with you as you go from room to room. The high frequency 2.4 GHz wireless transmission ensures you will get the clearest possible picture, over the maximum range allowed by FCC regulation. There are even 4 channels for you to choose from to get the clearest signal.

Audio monitoring is also included so that you can hear, as well as see, what’s going on. And with infrared illumination this even makes it possible for this system to see in the dark… perfect for nursery use.

HOME SENTINEL

Features:

- Complete video monitoring system includes both a 5” B/W monitor and wireless camera
- Camera uses IR illumination to provide a clear picture… even in the dark
- Audio monitoring function is included
- Up to 300’ (100 metres) line-of-sight range using high frequency 2.4 GHz transmission signal
- 4 channel switcher allows selection of the clearest channel for optimum reception
- Automatic cycling of all camera channels is possible, with manual override
- Standard RCA outputs for VCR recording connection
- Additional wired camera input on monitor
- Camera mounting bracket included

Monitor

300' Wireless Range

*In line-of-sight conditions

Camera/Transmitter

WO 500

2.4 GHz Wireless B/W Camera and 5” Monitor

Specifications:

Camera:		**Monitor:**	
Image sensor:	1/3” B/W CMOS	**Screen:**	5.5” diagonal CRT, 90° deflection
Resolution:	240 lines	**TV system:**	NTSC
No. of pixels:	76,000 pixels	**Hor. Resolution:**	300 lines
Illumination:	Infrared LED x 6	**Sensitivity:**	> -25 ~ 90 dBm
TV system:	NTSC	**Video output:**	1 Vp-p @ 75
Shutter:	1/60 ~ 1/6000 sec. (Auto)	**Audio output:**	400 mW (max.)
Backlight comp:	Yes	**Freq. range :**	2.400 ~ 2.4835 GHz (4 ch)
Output power:	0dBm (FCC)	**A/V modulation:**	FM
Freq. Range:	2.400 ~ 2.4835 GHz (4 ch)	**Antenna:**	Directional type
Power supply:	12VDC, 800mA adapter	**Power supply:**	13.5VDC, 1200mA adapter

Because our product is subject to continuous improvement, SVC reserves the right to modify product design and specifications without notice and without incurring any obligation, E & OE.

STRATEGIC vista

www.strategicvista.com

Corporate Information
300 Alden Road
Markham, Ontario
Canada L3R 4C1
Tel: (905) 946-8589
Fax: (905) 947-0138
info@strategicvista.com