INSTANT MOBILE VIEWING ON THE LOREX ECO LH100 SERIES

Using the Apple iPhone™

SOFTWARE GUIDE

English Version 1.0

LOREX®

www.lorexcctv.com

Copyright © 2009 Lorex Technology Inc.

MOBILE VIEWING ON YOUR IPHONE

Mobile viewing allows you to view video streams from your DVR (Digital Video Recorder) on your mobile device, such as an iPhone. It is an easy and convenient way to view events on your DVR.

Enabling Mobile Viewing On Your iPhone

To enable mobile viewing of your DVR, you will need an iPhone application called **Meye Sun**. This application can be downloaded through the Apple App Store™ on your iPhone. You need to create an iTunes™ account to access the App Store.

System Requirements	
Supported Devices	iPhone, iPod Touch with OS 2.2 or later
Storage Space	>800KB
Optional Software	iTunes

To download the Meye Sun application using your iPhone:

1. Touch the (App Store) icon to open the App store.
2. Touch the **Search** icon on the bottom of the screen. Search for **Meye Sun** and then touch the **Search** button.
3. Touch the **FREE** button, then touch **Install** to download and install the program.

The Meye Interface

Figure 1.0 The main interface window.

Icon	Function	Description
	Play	Connect to your cameras.
	Full Screen	Enable/disables full screen mode.
	Snap Shot	Takes a picture of the current channel.
	Settings	Set up your DVR's: IP address, port number, and account information.
	Next Group	View the next batch of cameras on your system (ranges from cameras 1~16).

Connecting To Your DVR

Once the application is installed on your phone, you can log in and access your system remotely.

Before You Start

- If you are connected to your service provider on your iPhone (ie. 3G network), you must enter in the WAN IP address of your DVR in the Settings window.
- To find the IP address of your DVR, press the ENTER button on the front panel.
- You must enable port forwarding on your DVR (Port 100).
- It is recommended to use a **static IP address.** If using a dynamic IP, your WAN IP may change frequently

NOTE: You must have access to the internet on your iPhone before you can connect to your cameras.

To connect to your cameras:

1. From your iPhone, touch the (Meye) icon to start the program.
2. Touch the (Settings) button. The setting window opens (Figure 1.2).
3. Under Server Info, in the Address field, enter your **DVR's WAN IP address** or a **DDNS*** address.In the Port field, enter your DVR's port number (default is port 100).
4. Under Account Info, in the User ID field, enter **admin**. In the Password field, enter **admin**.

   NOTE: You can only view a single channel at a time.
5. Touch the **Back** button to return to the main screen.
6. Touch the (play) icon to begin viewing. Touch the channel numbers on the bottom of the screen to switch channels.

Figure 1.2 Settings window.

*DDNS registration required.
See "Setting Up DDNS Service" on page 44 of your LH100 Series user's manual for details.

Uninstalling Meye From Your iPhone

To uninstall the Meye application from your iPhone:

1. From the iPhone's main menu, touch and hold the (Meye) icon for several seconds. Touch the **X** on the top left corner of the icon. A window opens that says, "Deleting "MEye" will also delete all of its data."
2. Touch the **Delete** button to uninstall the program.